

# Environment-resistant IP67 Power Supply S8NR-S

IP67-rated power supply enables easy implementation of power circuits outside control panels. A lineup of 90 W, 360 W, and 600 W models allows optimal power supply selection according to equipment scale.



For the most recent information on models that have been certified for safety standards, refer to your OMRON website

**Please refer to Power Supply Common Precautions and Safety Precautions on page 42.**

<Common Features (90 W/360 W/600 W)>

- Installation outside control panels shortens wiring distances, helping to reduce wiring and installation work.
- Compact and lightweight design allows flexible installation even in limited spaces.
- Smart click connectors simplify wiring work.

<Features of 360 W/600 W Models>

- Integrated package combining three functions: Power Supply, Protection, and Connection (Compact design and reduced wiring)
- Multiple electronic circuit protectors provided for multi-point protection
- Digital display enables monitoring of power circuit status without measurement (Output voltage, output current, remaining current, replacement notification, etc.)
- Remote parameter setting and monitoring via IO-Link communication
- Prevention of incorrect operation through key lock function and protection level settings

## Model Number Structure

### Model Number Legend

S8NR-□□□□□□-□□□□□□□□

Series 1 2 3 4 5

- |   |  |   |
|---|--|---|
| <p><b>1. Input Voltage Specification</b><br/>S: Single-phase Input</p> <p><b>2. Capacity</b><br/>090: 90 W<br/>360: 360 W<br/>600: 600 W</p> <p><b>3. Output Voltage</b><br/>24: 24 V</p> | <p><b>4. Number of output connectors</b><br/>A1L0: M12 A code: 1<br/>M12 L code: 0<br/>A0L2: M12 A code: 0<br/>M12 L code: 2<br/>A2L1: M12 A code: 2<br/>M12 L code: 1<br/>A0L3: M12 A code: 0<br/>M12 L code: 3<br/>A2L2: M12 A code: 2<br/>M12 L code: 2</p> | <p><b>5. IO-Link Specifications</b><br/>-IL3: IO-Link (COM3: 230.4 kbps)<br/>None: None</p> |
|---|--|---|

Smartclick is a trademark or registered trademark of OMRON Corporation in Japan and other countries.

Be sure to read and fully understand the content of the S8NR-S User's Manual (Man. No. T245) before changing settings on the S8NR-S.

# S8NR-S

## Ordering Information

### Main unit

Capacity	Input Voltage	Output Voltage	Maximum Tripping Output Current per a branch output	Output branch	Communication	Model
90 W	Single-phase 100 to 240 VAC	24 V	M12-A: 3.8 A M12-L: 10 A	---	---	<b>S8NR-S09024-A1L0</b>
360 W				2 connectors 4 outputs Connector 1: 10 A, 10 A Connector 2: 10 A, 10 A	IO-Link	<b>S8NR-S36024-A0L2-IL3</b>
	3 connectors 4 outputs Connector 1: 3.8 A (Class 2) Connector 2: 3.8 A (Class 2) Connector 3: 10 A, 10 A	<b>S8NR-S36024-A2L1-IL3</b>				
600 W	Single-phase 200 to 240 VAC	24 V	M12-A: 3.8 A M12-L: 10 A	3 connectors 6 outputs Connector 1: 10 A, 10 A Connector 2: 10 A, 10 A Connector 3: 10 A, 10 A	IO-Link	<b>S8NR-S60024-A0L3-IL3</b>
				4 connectors 6 outputs Connector 1: 3.8 A (Class 2) Connector 2: 3.8 A (Class 2) Connector 3: 10 A, 10 A Connector 4: 10 A, 10 A		<b>S8NR-S60024-A2L2-IL3</b>

### Mounting Brackets (Sold separately)

Name	Model
DIN-Rail mounting brackets (for S8NR-S09024)	<b>S82Y-NRS01DIN</b>
DIN-Rail mounting brackets (for S8NR-S36024 and S8NR-S60024)	<b>S82Y-NRS02DIN</b>

### Waterproof Caps (Sold separately)

Name	Model
Waterproof caps for socket connectors	<b>XS5Z-12</b>
Waterproof caps for plug connectors	<b>XS5Z-13</b>

## Specifications

## S8NR-S09024-A1L0

Model		S8NR-S09024-A1L0	
Efficiency *1	100 VAC Input *1	91% typ.	
	200 VAC Input *1	93% typ.	
Input conditions	Input voltage allowable range *3	85 to 264 VAC	
	Frequency *3	50/60 Hz(47 to 63 Hz)	
	Input current	1.2 A max. (100 VAC input) 0.6 A max. (200 VAC input)	
	Power factor *1	0.9 min.	
	Leakage current	0.5 mA max. (100 VAC input)	
		1 mA max. (200 VAC input)	
Inrush current (for a cold start at 25°C)	14 A typ. (100 VAC input)		
	28 A typ. (200 VAC input)		
Output characteristics	Rated output current	3.8 A	
	Rated output electric power	91.2 W	
	Maximum boost current	---	
	Voltage variable range	No voltage adjustment	
	Ripple noise voltage *1	100 mV p-p max. (at rated input and outputs)	
	Static input fluctuation	0.5% or less (at input 85 to 264 VAC, 100% load) *2	
	Load fluctuation	1.5% or less (at rated input, 0 to 100% Load) *2	
	Ambient temperature fluctuation	0.05%/°C max.	
	Startup time *5	1,000 ms max *1	
	Outputs hold time *5	30 ms typ. (at rated input and outputs) *1	
Functions	Overload protection	Yes, automatic reset	
	Overvoltage protection	Yes, 130% or higher of rated output voltage, power shut off (shut off the input voltage and turn on the input again)	
	Series connection	Not supported.	
	Parallel connection	Not supported.	
	Output indicator	Provided (Color: green)	
DC OK Signal Output	Yes (MOS FET relay output 30 VDC max., 50 mA max.)		
Withstand voltage	Dielectric strength voltage	2 kVAC for 1 min between (input terminals pins 1 and 3 collectively) and (PE ⊕, output terminals and signal terminals collectively) Detection current: 20 mA	
		500 VAC for 1 min between (output terminals collectively) and (signal terminals collectively) Detection current: 10 mA	
Insulation resistance	100 MΩ min. at 500 VDC between (input terminals pins 1 and 3 collectively) and (PE ⊕, output terminals and signal terminals collectively)		
Environment	Ambient operating temperature	-25 to 70°C (with no condensation or icing) *4	
	Storage temperature	-25 to 85°C	
	Ambient operating humidity	5 to 95%	
	Storage humidity	5 to 95%	
	Vibration resistance	10 to 55 Hz, 0.375 mm single amplitude, 2h each in X, Y, and Z directions, maximum 4.5G	
	Shock resistance	150 m/s <sup>2</sup> 3 times each in ±X, ±Y, ±Z directions.	
Reliability	MTBF	135,000 hrs min.	
	Expected life	10 years	
Construction	Weight (main unit)	650 g max	
	Cooling fan	blank	
	Protective structure *8	IP67, UL Type1	
Compatible standards	Harmonic suppression		
	EMI	Conducted EMI	Compliant with EN 61204-3 Class B, EN 55011 Class B
		Radiated EMI	Compliant with EN 61204-3 Class B, EN 55011 Class B
	EMS	EN 61204-3 high severity levels	
	Safety standards	UL 508 (Listing, Class2 Output: Per UL 1310), Pol3 EN/IEC 62477-1 (ES1 Output), OVCIII (<2,000 m), OVCI (2,000 m<and<3,000 m), Pol3 RCM (EN 61000-6-4) PELV (EN/IEC 60204-1)	

Note: Refer to page 19 for \*1 to \*8.

## S8NR-S36024-A□L□-IL3

Model		S8NR-S36024-A0L2-IL3	S8NR-S36024-A2L1-IL3	
Efficiency *1	100 VAC Input *1	92% typ. (Power supply section only: 94% typ.)		
	200 VAC Input *1	94% typ. (Power supply section only: 96% typ.)		
Input conditions	Input voltage allowable range *3	85 to 264 VAC		
	Frequency *3	50/60 Hz (47 to 63 Hz)		
	Input current	4.0 A typ. (100 VAC input) 2.0 A typ. (200 VAC input)		
	Power factor	0.9 min.		
	Leakage current	0.5 mA max. (100 VAC input)		
		1 mA max. (200 VAC input)		
	Inrush current (for a cold start at 25°C)	7 A typ. (100 VAC input)		
14 A typ. (200 VAC input)				
Output characteristics	Number of branches	4 (M12-L×2)	4 (M12-A×2, M-12L×1)	
	Maximum cutoff output current (per branch)	M12-A: 3.8 A (Class 2 Output) M12-L: 10 A		
	Total output current	15 A		
	Voltage variable range	24 to 28 V (adjustable with HMI or IO-Link communication)		
	Ripple noise voltage (at rated input and outputs) *1	130 mV p-p max. (at 20 MHz of bandwidth)		
	Output leakage current	10 mA max.		
	Static input fluctuation	0.5% or less (at input 85 to 264 VAC, 100% load) *2		
	Load fluctuation	4.0% or less (at rated input, 0 to 100% Load) *2		
	Ambient temperature fluctuation	0.05%/°C max.		
	Startup time *5	2,000 ms max *1		
	Outputs hold time *5	45 ms typ. (at rated input and outputs) *1		
	Functions	Tripping functions	Abnormal voltage tripping	24.0 to 32.0 V (in 0.1 V unit)
			Abnormal current tripping *2	Setting range: M12-A: 0.5 to 3.8 A (in 0.1 A unit), M12-L: 0.5 to 10 A (in 0.1 A unit)
Abnormal total current tripping			The output is shut off when the total output current reaches 30 A for 1 s, 26 A for 2 s, 22.5 A for 5 s, 19.5 A for 10 s, or 18 A for 20 s.	
Undervoltage detection functions		Undervoltage Detection	Setting range: 18.0 to 28.0 V (in 0.1 V unit)	
Maintenance forecast monitor function		Years up to replacement time	Setting range: 0.0 to 5.0 yr (in 0.5 yr unit)	
		Percentage up to replacement time	Setting range: 0.0 to 99.9% (in 0.1% unit)	
		Total running time	Setting range: 0 to 132 kh (in 1 kh unit)	
Display functions		Output voltage display	Display range: 16.3 to 30.0 V Display accuracy: 2% rdg ±1 digit max.	
		Output current display	Branch output current display range: 0.0 to 4.0 A (M12-A), 0.0 to 10.0 A (M12-L), Branch output peak current display range: 0.0 to 20.0 A Total output current display range: 0.0 to 40.0 A Display accuracy: M12-A 5% FS (4 A) ±1 digit max. M12-L 5% FS (10 A) ±1 digit max.	
		Maintenance forecast monitor display (yr)	Display range: FUL (Full)/HLF (Half)/0.0 to 5.0 yrs	
		Maintenance forecast monitor display (percentage)	Display range: 0.0 to 99.9%	
		Total running time	Display range: 0 to 256 kh	
Startup sequence		Setting range: 0.0 to 99.9 seconds (0.1-second Unit) Default Branch output 1: 0.0 s Branch output 2: 0.4 s Branch output 3: 0.8 s Branch output 4: 1.2 s		
Shutdown sequence		Setting range: 0.0 to 99.9 s (0.1 s Unit)		

Note: Refer to page 19 for \*1 to \*8.

Model		S8NR-S36024-A0L2-IL3	S8NR-S36024-A2L1-IL3	
Functions	Series connection	Not supported.		
	Parallel connection	Not supported.		
	Output indicator	Provided (Color: green)		
	Indication monitor	Measurement/ displayed details	For details, refer to <i>S8NR-S Users Manual</i> (Man. No. T245).	
		Main display area	11-segment display (Color: white)	
Channel display area		Seven-segment display (Color: green)		
	Unit display area	Provided (Color: yellow)		
Withstand voltage	Dielectric strength voltage	2 kVAC for 1 min between (input terminals pins 1 and 3 collectively) and (PE ⊕, branch output terminals and IO-Link communications terminals collectively) Cutoff current: 20 mA		
	Insulation resistance	100 MΩ min. at 500 VDC between (PE ⊕, branch output terminals and IO-Link communication terminals collectively) and (input terminals pins 1 and 3 collectively)		
Environment	Ambient operating temperature	-25 to 70°C (with no condensation or icing) *4		
	Storage temperature	-25 to 85°C		
	Ambient operating humidity	5 to 95%		
	Storage humidity	5 to 95%		
	Vibration resistance	10 to 55 Hz, 0.375 mm single amplitude, 2h each in X, Y, and Z directions, maximum 4.5G		
	Shock resistance	150 m/s <sup>2</sup> 3 times each in ±X, ±Y, ±Z directions.		
Reliability	MTBF	36,000 hours min.		
	Expected life	10 years		
Construction	Weight (main unit)	1,800 g max		
	Cooling fan	blank		
	Protective structure (dustproof and waterproof) *8	IP67, UL Type1		
Compatible standards	Harmonic suppression	Conforms to EN61000-3-2		
	EMI	Conducted EMI	Compliant with EN 61204-3 Class B, EN 55011 Class B	
		Radiated EMI	Compliant with EN 61204-3 Class B, EN 55011 Class B *7	
	EMS	EN 61204-3 high severity levels		
	Safety standards	UL 508 (Listing, Class2 Output: Per UL 1310), Pol3 *6 CSA C22.2 No.107.1 (Class2 Output: Per CSA C22.2 No.223), Pol3 *6 EN/IEC 62477-1 (ES1 Output), OVCIII (<2,000 m), OVCII (2,000 m< and <3,000 m), Pol3 RCM (EN 61000-6-4) PELV (EN/IEC 60204-1)		

Note: Refer to page 19 for \*1 to \*8.

## S8NR-S60024-A□L□-IL3

Model		S8NR-S60024-A0L3-IL3	S8NR-S60024-A2L2-IL3
Efficiency *1	200 VAC input *1	94% typ. (Power supply section only: 95% typ.)	
Input conditions	Input voltage allowable range *3	170 to 264 VAC	
	Frequency *3	50/60 Hz (47 to 63Hz)	
	Input current	3.2 A typ. (200 VAC input)	
	Power factor	0.9 min.	
	Leakage current	1 mA max. (200 VAC input)	
	Inrush current (for a cold start at 25°C)	14 A typ. (200 VAC input)	
Output characteristics	Number of branches	6 (M12-L×3)	6 (M12-A×2, M-12L×2)
	Maximum cutoff output current (per branch)	M12-A: 3.8 A (Class 2 Output) M12-L: 10 A	
	Total output current	25 A	
	Voltage variable range	24 to 28 V (adjustable with HMI or IO-Link communication)	
	Ripple noise voltage (at rated input and outputs) *1	180 mV p-p max. (at 20 MHz of bandwidth)	
	Output leakage current	10 mA max.	
	Static input fluctuation	0.5% or less (at input 170 to 264 VAC, 100% load) *2	
	Load fluctuation	4.0% or less (at rated input, 0 to 100% Load) *2	
	Ambient temperature fluctuation	0.05%/°C max.	
	Startup time *5	2,000 ms max *1	
	Outputs hold time *5	20 ms typ. (at rated input and outputs) *1	
	Functions	Tripping functions	Abnormal voltage tripping
Abnormal current tripping*2			Setting range: M12-A: 0.5 to 3.8 A (in 0.1 A unit), M12-L: 0.5 to 10 A (in 0.1 A unit)
Abnormal total current tripping			The output is shut off when the total output current reaches 43.5 A for 2 s, 37.5 A for 5 s, 32.5 A for 10 s, or 30 A for 20 s
Undervoltage detection functions		Undervoltage Detection	Setting range: 18.0 to 28.0 V (in 0.1 V unit)
Maintenance forecast monitor function		Years up to replacement time	Setting range: 0.0 to 5.0 yr (in 0.5 yr unit)
		Percentage up to replacement time	Setting range: 0.0 to 99.9% (in 0.1% unit)
		Total running time	Setting range: 0 to 132 kh (in 1 kh unit)
Display functions		Output voltage display	Display range: 16.3 to 30.0 V Display accuracy: 2% rdg ±1 digit max.
		Output current display	Branch output current display range: 0.0 to 4.0 A (M12-A), 0.0 to 10.0 A (M12-L), Branch output peak current display range: 0.0 to 20.0 A Total output current display range: 0.0 to 40.0 A Display accuracy: M12-A 5% FS (4 A) ±1 digit max. M12-L 5% FS (10 A) ±1 digit max.
		Maintenance forecast monitor display (yr)	Display range: FUL (Full)/HLF (Half)/0.0 to 5.0 yrs
		Maintenance forecast monitor display (percentage)	Display range: 0.0 to 99.9%
		Total running time	Display range: 0 to 256 kh
Startup sequence		Setting range: 0.0 to 99.9 seconds (0.1-second Unit) Default Branch output 1: 0.0 s Branch output 2: 0.4 s Branch output 3: 0.8 s Branch output 4: 1.2 s Branch output 5: 1.6 s Branch output 6: 2.0 s	
Shutdown sequence		Setting range: 0.0 to 99.9 s (0.1 s Unit)	

Note: Refer to page 19 for \*1 to \*8.

Model		S8NR-S60024-A0L3-IL3	S8NR-S60024-A2L2-IL3	
Functions	Series connection	Not supported		
	Parallel connection	Not supported		
	Output indicator	Provided (Color: green)		
	Indication monitor	Measurement/ displayed details	For details, refer to <i>S8NR-S Users Manual</i> (Man. No. T245).	
		Main display area	11-segment display (Color: white)	
Channel display area		Seven-segment display (Color: green)		
	Unit display area	Provided (Color: yellow)		
Withstand voltage	Dielectric strength voltage	2 kVAC for 1 min between (input terminals pins 1 and 3 collectively) and (PE ⊕, branch output terminals and IO-Link communications terminals collectively) Cutoff current: 20 mA		
	Insulation resistance	100 MΩ min. at 500 VDC between (PE ⊕, branch output terminals and IO-Link communication terminals collectively) and (input terminals pins 1 and 3 collectively)		
Environment	Ambient operating temperature	-25 to 70°C (with no condensation or icing) *4		
	Storage temperature	-25 to 85°C		
	Ambient operating humidity	5 to 95%		
	Storage humidity	5 to 95%		
	Vibration resistance	10 to 55 Hz, 0.375 mm single amplitude, 2h each in X, Y, and Z directions, maximum 4.5G		
	Shock resistance	150 m/s <sup>2</sup> 3 times each in ±X, ±Y, ±Z directions.		
Reliability	MTBF	36,000 hours min.		
	Expected life	10 years		
Construction	Weight (main unit)	1,800 g max		
	Cooling fan	blank		
	Protective structure (dustproof and waterproof) *8	IP67, UL Type1		
Compatible standards	Harmonic suppression	Conforms to EN61000-3-2		
	EMI	Conducted EMI	Compliant with EN 61204-3 Class B, EN 55011 Class B	
		Radiated EMI	Compliant with EN 61204-3 Class B, EN 55011 Class B *7	
	EMS	EN 61204-3 high severity levels		
	Safety standards	UL 508 (Listing, Class2 Output: Per UL 1310), Pol3 *6 CSA C22.2 No.107.1 (Class2 Output: Per CSA C22.2 No.223), Pol3 *6 EN/IEC 62477-1 (ES1 Output), OVCIII (<2,000 m), OVCII (2,000 m< and <3,000 m), Pol3 RCM (EN 61000-6-4) PELV (EN/IEC 60204-1)		

\*1. Rated input/output conditions: at rated input voltage, rated frequency, rated output voltage, rated total output current, and maximum cutoff output current.

\*2. 100% Load condition: at rated output voltage, rated total output current and maximum cutoff output current.

\*3. Although some inverters have an output frequency of 50/60 Hz, they may cause internal temperature to rise and result in damage, if they are connected as the power source for the S8NR-S. Do not use the output from an inverter as the power source for the S8NR-S.

\*4. For details, refer to *Derating curve* on page 27.

\*5. For details, refer to *Inrush current, startup time, Outputs hold time* on page 45.

\*6. Class2 Output is only for M12-A output

\*7. When IO-Link communication is used, this product is classified as Class A.

\*8. With waterproof caps attached to unused terminals.

**IO-Link Specifications**

Item	Description
IO-Link Specifications	Ver 1.1.4
Baud rate	COM3: 230.4 kbps (fixed)
Device profile	Common Profile, Locator
Minimum cycle time	COM3: 2.0 ms
Data length	PD size: 22 byte OD size: 1 byte (M-sequence type: TYPE_2_V)
Port class	ClassA

Please contact your OMRON sales representative regarding the IO-Link setup file (IODD file).

**IO-Link Indicator LEDs**

The LED indications are prioritized in the order listed from top to bottom in this table.  
When multiple statuses occur simultaneously, the indication listed higher in the table is displayed.

Indicator	Status	Description
Green flashing (fast)	Locator active	Flashes twice and then turns OFF repeatedly at a 1-second cycle for 10 minutes. This function allows the product to be visually identified among multiple devices at the installation site. For start/stop commands, refer to 5-2 <i>IO-Link Communication Index List, Index 2 (System Command)</i> in the <i>S8NR-S Users Manual</i> (Man. No. T245)
Red ON	Internal fault	An internal failure may have occurred in the product. Restart the product. If the error reoccurs, replace the product.
Green flashing	Communication established	IO-Link communication is established.
OFF	Communication not established	No IO-Link communication.


**IO-Link Communication Index List**

Refer to the *S8NR-S Users Manual* (Man. No. T245) for IO-Link communication Index list.


Connection

Block Diagrams

S8NR-S09024-A1L0




S8NR-S36024-A0L2-IL3




S8NR-S

S8R-BB


S8NR-S36024-A2L1-IL3



S8NR-S60024-A0L3-IL3



S8NR-S60024-A2L2-IL3




S8NR-S

S8R-BB

Nomenclature

S8NR-S09024-A1L0




No.	Connector Name	Shape	Pin Assignment
(1)	Input Terminal M12-S (Plug)		PE: PE (Protective Earth) Terminal *1 ⊕ 1: Input Terminal (L) 3: Input Terminal (N)
(2)	Output Terminals M12-A (Socket)		1: Output Terminal (+) (Class 2 Output) 2: NC 3: Output Terminal (-) (Class 2 Output) 4: NC 5: NC
(3)	Signal Terminal M12-A (Plug)		1: Signal Output (DC OK1) Non-polarized 2: No Pin 3: No Pin 4: Signal Output (DC OK2) Non-polarized
(4)	PE Terminal (⊕)		Recommended screws: M4 Recommended tightening torque: 0.7 N·m Recommended wire: AWG14
(5)	Output Indicator (DC OK (Green))		Indicates whether output voltage is supplied.

\*1. As this is a PE (Protective Earth) terminal specified by safety standards, ensure it is connected to ground.

S8NR-S36024-A□L□-IL3

S8NR-S60024-A□L□-IL3

The following explanation uses the connector layout of S8NR-S60024-A2L2-IL3 as a representative example. Refer to the user manual for details.




No.	Connector Name	Shape	Pin Assignment
(1)	Input Terminal M12-S (Plug)		PE: PE (Protective Earth) Terminal *1 ⊕
			1: Input Terminal (L)
			3: Input Terminal (N)
(2)	Output Terminals M12-L (Socket)		FE: FE (Functional Earth) Terminal ⚡
			1: Branch Output Terminal (+) (1/2)
			2: Branch Output Terminal (-) (2/2)
			3: Branch Output Terminal (-) (1/2)
(3)	Output Terminals M12-A (Socket)		4: Branch Output Terminal (+) (2/2)
			1: Branch Output Terminal (+) (Class 2 Output)
			2: NC
			3: Branch Output Terminal (-) (Class 2 Output)
			4: NC
(4)	IO-Link Communication Terminal M12-A (Plug)		5: NC
			1: L+
			2: No Pin
			3: L-
(5)	PE Terminal		4: C/Q
			Recommended screws: M4 Recommended tightening torque: 0.7 N·m Recommended wire: AWG14
(6)	Key Lock Indicator		Lights when key lock is active.
	Output Indicator (DC OK (Green))		Indicates whether output voltage is supplied.
(7)	Mode Display (MON/SET)		Displays the current mode (Monitor Mode/Setting Mode).
(8)	Branch Output Number Indicator (Green)		Displays the currently selected branch output channel.
(9)	Eleven-segment Display (White)		Displays measured or set values.
(10)	Unit Indicator (Orange)		Lights when the displayed value on the Eleven-segment Display relates to units (TOTAL, OUTPUT, V, A, Apk, Arm, Yrs, %, kh, sec).
	Mode Switch Key		Switches between Monitor Mode and Setting Mode.
	Channel Down Key		Used to switch branch outputs.
	Channel Up Key		
	Select Down Key		Used to scroll forward through display items or decrease a set value.
	Select Up Key		Used to scroll backward through display items or increase a set value.
	Enter Key		Switches between display items and confirms or executes settings.
Reset (RST)/ Cancel (ESC) Key		Switches between display items and cancels operations. It also releases abnormal conditions when abnormal shutdown operations or alarm outputs are active.	
(11)	Channel ON/OFF Key (Red/ Green)		Indicator shows connection/tripping status for each branch output: Red=Tripped, Green=Connected. *2 The push button toggles connection/tripping for each branch output. For 360 W models, channels are limited to CH1 to CH4.
(12)	IO-Link Indicator (Red/Green)		In case of a product fault, the indicator lights solid red. Under normal conditions, the indicator is off when communication is not established, and blinks green once communication is established.

\*1. As this is a PE (Protective Earth) terminal specified by safety standards, ensure it is connected to ground.


\*2. For details on the display method, refer to *Operation display and how to operate the Channel ON/OFF key* on page 35.

# Channel Assignment for Output Terminal Connectors


## S8NR-S09024-A1L0




## S8NR-S36024-A2L1-IL3




## S8NR-S60024-A2L2-IL3



## S8NR-S36024-A0L2-IL3



## S8NR-S60024-A0L3-IL3




# Characteristic Data


## Derating curve

The allowable ambient temperature of the S8NR-S is determined by the rated output current (90 W) or the maximum total output current under normal operating conditions (360 W and 600 W), as indicated by the derating curve.  
At least 15 mm spacing between left and right during standard installation

S8NR-S09024-A1L0




S8NR-S36024-A□L□-IL3  
S8NR-S60024-A□L□-IL3




**Note: 1.** Please multiply the Load factor indicated by the above Outputs derating by the Load reduction coefficient relative to the input voltage and use the resulting value.

## Load reduction factor for input voltage


S8NR-S09024-A1L0, S8NR-S36024-A□L□-IL3



S8NR-S60024-A□L□-IL3




This Power Supply can be used at an altitude of 3,000 m. Between 2,000 and 3,000 m, derate the load according to the following derating curve.  
Horizontal separation: 15 mm or more




**Note: 1.** Please multiply the Load factor indicated by the above Outputs derating by the Load reduction coefficient relative to the input voltage and use the resulting value.

## Load reduction factor for input voltage

S8NR-S09024-A1L0, S8NR-S36024-A□L□-IL3



S8NR-S60024-A□L□-IL3



### DC OK Signal Output Function

When the output voltage is 90% or more of the rated output voltage, the internal MOS FET relay turns ON (conducts).

**Note: 1.** The DC OK signal output function monitors the voltage at the product's output terminals.  
To check the exact voltage applied to the load, measure the voltage at the load terminals.

### Specifications

The signal output consists of a MOSFET relay. Polarity is not required.

30 VDC max.

50 mA max.

Residual voltage when ON: 2 V max

Leakage current when OFF: 0.1 mA max

**Note: 2.** Internal current control circuits are not provided internally for output signals. Do not allow the output current to exceed 50 mA.

**Note: 3.** After completing wiring, confirm that the circuits operate correctly.

## Functions <S8NR-S36024-A□L□-IL3, S8NR-S60024-A□L□-IL3>

### Abnormal Current Tripping Characteristics Functions

The current tripping characteristics can be selected from three types of Tripping type: Standard Detection, Instantaneous Detection, and Extended Detection. For details, please refer to the *Form S8NR-S Users Manual* (Man. No. T245).

**Note 1.** In the event of an abnormal tripping, be sure to reset and restore the system only after the cause has been eliminated.

**Note 2.** When using loads that operate with constant power, tripping may occur when the power is turned off.

**Note 3.** The current tripping accuracy is within  $\pm 0.3$  A of the Set value.

#### Current limiting by internal circuits


S8NR-S has a current Restrictions circuit inside to prevent a current exceeding a certain level from flowing. Until the tripping time is reached, the current is Restrictions by this characteristic.

#### Short-circuit Protection Fuse


If, due to some abnormality, the branch output cannot be tripping off by the tripping circuit, the short-circuit protection fuse will blow to protect the circuit.

**Note:** If the fuse blows, that branch output cannot be used.


#### Standard Detection (M12-A)




#### Standard Detection (M12-L)




#### Extended Detection (M12-A)




#### Extended Detection (M12-L)



#### Instantaneous Detection (M12-A)



#### Instantaneous Detection (M12-L)



## Tripping Functions

Settings	Operating range	Parameters settings	Outputs cutoff
Abnormal Voltage Tripping	Tripping when the output voltage exceeds the abnormal voltage tripping setting.	Yes	All branch outputs
Short-circuit current tripping	The cutoff current varies depending on the output connector. M12-A: Cutoff at 16 A within 20 ms, and at 11 A within 60 ms. M12-L: Cutoff at 16 A within 20 ms, and at 13 A within 60 ms.	None	Individual branch output
Abnormal total current tripping	Tripping occurs when the sum of all branch output currents exceeds at a constant current value for a certain period of time.	None	All branch outputs
Abnormal current tripping *1	The setting range varies depending on the output connector. M12-A: 0.5 to 3.8 A (in 0.1-A increments) M12-L: 0.5 to 10.0 A (in 0.1-A increments) Select from standard, instantaneous, and extended detection methods.	Yes	Individual branch output
Cutoff by IO-Link external signal input	Refer to <i>Index 124: External tripping input cutoff for branch</i> or <i>Index 125: External tripping input</i> in the <i>S8NR-S Users Manual</i> (Man. No. T245)	Yes	Specified output *2

\*1. The tripping function operates within 100 ms when the S8NR-S is set to standard detection, within 20 ms when it is set to instantaneous detection, and within 1,000 ms when it is set to extended detection.

\*2. Only branch outputs with Tripping Operation via External Tripping Input set to "Enabled" are affected.  
(Refer to 2-7 *External Signal Tripping Input* function in the *S8NR-S Users Manual* (Man. No. T245))

## Voltage Adjustment Function

The output voltage can be adjusted by key operation or via communication. The adjustable range is from 24.0 V to 28.0 V.

### Adjustment by Key Operation

1. Press the Mode Select key to enter the setting mode. **SET** is in the setting mode when the indicator is lit.



2. The output voltage value is displayed.

3. Press the Enter key (↵).

4. Use the Select Up key (⬆) or Select Down key (⬇) to adjust to the desired voltage.

### Adjustment via Communication

For adjustment via communication, refer to *S8NR-S User's Manual* (Man. No. T245).

## Remaining Current Value Function

The Remaining Current Value function displays how much current can still be supplied for each branch output. This function allows users to monitor the remaining current of each branch output and perform appropriate current management, helping to prevent overloads and abnormal currents and ensuring safe operation.

For details, refer to *S8NR-S User's Manual* (Man. No. T245).

## Stress Level Function

This function indicates how much of the total capacity is currently being used.

For details, refer to *S8NR-S User's Manual* (Man. No. T245).

## Standby Function

Based on commands received via communication, this function controls enabling and disabling of the 24 V output.

Settings can be configured only via IO-Link.

For details, refer to *S8NR-S User's Manual* (Man. No. T245).

## Maintenance Forecast Monitor Function

This product has a built-in electrolytic capacitor. Electrolytic capacitors undergo degradation in characteristics, such as a decrease in capacitance, over time due to the evaporation of the internal electrolyte solution. This degradation begins at the time of manufacture as the impregnated electrolyte solution permeates the sealing rubber. Due to degradation of this electrolytic capacitor's characteristics, this product will become unable to perform sufficiently over time. The maintenance forecast monitor function calculates an estimated period until this product will no longer be able to perform sufficiently due to degradation of the electrolytic capacitor's characteristics. This feature can be used as a guideline for finding out when to replace the product main unit.

**Note:** The maintenance forecast monitor function indicates an estimated period until the product will no longer be able to perform sufficiently due to degradation of the electrolytic capacitor. This function does not cover failures caused by other factors.

### Principle of Operation

The degradation rate of an electrolytic capacitor varies considerably with ambient temperature (generally following the doubling for every 10°C rule and the Arrhenius equation).

The S8NR-S monitors the internal temperature of the product while powered ON, and calculates the degradation level of the electrolytic capacitor based on running time and internal temperature.

**Note: 1.** Depending on the durability of the electronic components, we recommend replacing the electrolytic capacitors approximately 15 years after purchase, regardless of the maintenance forecast monitor number of years or percentage displayed.

**Note: 2.** The replacement time varies depending on changes in operating conditions. Check the display periodically.

**Note: 3.** In applications where the input power is frequently turned ON and OFF, the accuracy of the maintenance forecast monitor function may deteriorate.

### Years up to replacement time


*FUL* is indicated at the time of purchase (when initially powered on), and continues to be indicated for approximately one month.

Afterward, the state of deterioration for the electrolytic capacitor is calculated based on the usage environment and *HLF* is indicated when deterioration progresses. When the years until replacement reaches 5 years or less, it is indicated in 0.1 step increments within the range of 4.9 to 0.0. (Depending on the usage environment, the number of years may be indicated after *FUL* without *HLF* being indicated.)

**Note:** The number of years until replacement may vary if there are frequent load variations or in locations where the ambient temperature fluctuates drastically.

### Percentage up to replacement time

With the number of years until replacement at the time of manufacture set as 100%, as deterioration of the electrolytic capacitor progresses through use, it decreases in 0.1% step increments.



Relationship between electrolytic capacitor power rating and indicator

## Pre-warning Function

When the current of each branch output or the total current exceeds the set value of the PSU current pre-warning level, warning information is issued. Settings and notifications can be configured only via communication (IO-Link).


For details, refer to *S8NR-S User's Manual* (Man. No. T245).

### Total running time

The accumulated value of the product's time powered on is measured as the total run time.

The Total run time increases in 1 (kh) steps.

### Time Chart



**Note: 1.** The total run time does not include the time that the Power Supply is OFF.

**Note: 2.** The total run time measures the total time that power is being supplied and is not related in any way to deterioration in the electrolytic capacitor built into the Power Supply or to the effects of the ambient temperature.


### Maintenance Forecast Monitor Output (A23) Displayed

When error code A23 (maintenance forecast monitor output) is displayed on the eleven-segment display, it indicates that the replacement time calculated by the S8NR-S has fallen below the set value. The number of years left before replacement is required will be displayed in half-year increments. Prepare to replace the Power Supply.

### Startup Sequence Function

The inrush current may cause a voltage drop if all of the branch outputs are connected simultaneously and there is little spare capacity in the power supply or the loads connected to the branch outputs are capacitive loads. A significant voltage drop may cause an output to be cut off. In this case, a time delay can be applied between the connections of the branch outputs to minimize the voltage drop.

- Note: 1.** The time delay can be set between 0.0 and 99.9 s. (If the delay is set to 0.0 s, the startup sequence will not operate and the branch output will be connected immediately.)
- Note: 2.** The sequence Functions is only guaranteed between individual Branch output. When using multiple S8NR-S units, time synchronization between each S8NR-S unit cannot be maintained.




- The branch output's status indicator will flash green during the startup sequence time until it is connected.
- For details on verification of the startup sequence, refer to the *S8NR-S User's Manual* (Man. No. T245).
- The default values of the startup sequence for each branch output are set as follows.

Branch Output No.	1	2	3	4	5	6
Setting time (360 W)	0.0 s	0.4 s	0.8 s	1.2 s	---	---
Setting time (600 W)	0.0 s	0.4 s	0.8 s	1.2 s	1.6 s	2.0 s

### Shutdown Sequence Function

When the S8NR-S's input power supply is turned OFF, all of the branch outputs are turned OFF (disconnected) simultaneously. On the other hand, when the branch outputs are cut off by the external tripping input or communications, a time delay can be applied between the branch output disconnections.

- Note: 1.** The time delay can be set between 0.0 and 99.9 s. (If the delay is set to 0.0 s, the startup sequence will not operate and the branch output will be cut off immediately.)
- Note: 2.** The sequence functions is only guaranteed between individual Branch output. When using multiple units of the S8NR-S model, time synchronization between each S8NR-S model cannot be achieved.



- Note: 3.** When operation is cut off due to an abnormal voltage, all of the branch outputs will be cut off simultaneously.
- Note: 4.** The shutdown sequence function will operate on a branch output only if the external tripping input is enabled for that branch output. For details, refer to the *S8NR-S User's Manual* (Man. No. T245).

- For details on verification of the shutdown sequence, refer to the *S8NR-S User's Manual* (Man. No. T245).

## Monitoring Functions

Parameter name	Details	Display	Communication
Output voltage (Index 79: Present Voltage Value)	Displays the output voltage.	Yes	Yes
Output current (Index 84: Output Current)	Displays the current value of each branch output.	Yes	Yes
Total current (Index 81: Total Current)	Displays the total current value of all the branch outputs.	Yes	Yes
Peak current (Index 89: Peak Current Value)	Displays individual branch output peak currents.	Yes	Yes
Remaining Current Value (Index 90: Remaining Current Value)	Displays how much additional current can be supplied for each branch output.	Yes	Yes
Years up to replacement time (Index 67: Remaining Current Value)	Displays the remaining number of years up to the replacement time by forecasting the replacement time of the S8NR-S.	Yes	Yes
Percentage up to replacement time (Index 68: Percentage up to replacement time)	Displays the remaining number of percentage up to the replacement time by forecasting the replacement time of the S8NR-S.	Yes	Yes
Total running time (Index 73: Total running time)	Displays the total operating time of the S8NR-S unit.	Yes	Yes
Temperature (Index 69: Internal Temperature)	Displays the internal temperature of the S8NR-S.	None	Yes

## Setting Functions

Parameter Name	Description	Display	Communication
Output Voltage Setting (Index 105: Output Voltage Setting Value )	Allows adjustment of the output voltage. The adjustable range is from 24.0 to 28.0 V.	Yes	Yes
Abnormal Current Tripping Threshold (Index 108: Abnormal Current Tripping Threshold)	Allows setting of the tripping current value for each branch output. The setting resolution is 0.1 A.	Yes	Yes
Abnormal Current Tripping Detection Type (Index 107: Abnormal Current Tripping Detection Type)	Allows selection of the shutdown detection method for each branch output. USU: Standard (tripping within 100 ms) INS: Instantaneous (tripping within 20 ms) LNG: Long-time (tripping within 1,000 ms)	Yes	Yes
Abnormal Voltage Tripping Threshold (Index 112: Abnormal Voltage tripping Threshold)	Allows setting of the abnormal voltage tripping threshold for the output voltage.	Yes	Yes
Undervoltage Alarm Threshold (Index 114: Undervoltage Alarm Threshold)	Detects a drop in output voltage and displays an undervoltage alarm ( $R2$ !). The event is also output via IO-Link communication. Setting resolution is 0.1 V. Branch outputs are not shut down.	Yes	Yes
Years-to-Replacement Alarm Threshold (Index 116: Years-to-Replacement Alarm Threshold)	Sets the planned replacement years for the S8NR-S unit. When the value falls below the threshold, the "Yrs" indicator lights once. The event is also output via IO-Link communication.	Yes	Yes
Replacement Ratio Alarm Threshold (Index 117: Replacement Ratio Alarm Threshold)	Sets the planned replacement ratio for the S8NR-S unit. When the value falls below the threshold, the "%" indicator lights once. The event is also output via IO-Link communication.	Yes	Yes
Operating Time Alarm Threshold (Index: 118)	Sets the operating time alarm threshold. When exceeded, the "kh" indicator lights once. The event is also output via IO-Link communication.	Yes	Yes
Temperature Alarm Threshold (Index 115: Temperature Alarm Threshold)	Allows setting of a temperature alarm by detecting an increase in the internal temperature of the S8NR-S unit.	None	Yes
Startup Sequence (Index 110: Startup Sequence )	Allows a time delay to be set for each branch output when connection starts at power ON. This enables sequence operation and disperses inrush current, reducing the load on the power supply.	Yes	Yes
Shutdown Sequence (Index: 111)	Allows a time delay to be set when shutting down branch outputs via an external signal tripping input from communication.	Yes	Yes
Shutdown Trigger Enable/Disable (Index 125: External)	Allows enabling (ON) or disabling (OFF) the external shutdown signal input via communication for each branch output.	None	Yes
Shutdown Trigger Input Type (Index: 123)	Allows setting the type of shutdown trigger input commonly used for branch outputs where the shutdown trigger input is enabled.	None	Yes

Parameter Name	Description	Display	Communication
Reset Function Setting (Index 119: Alarm Reset Setting)	Selects the reset operation method to recover from an abnormal tripping or alarm state after the cause has been removed. <ul style="list-style-type: none"> <li>• KEY: Only the RST key is enabled.</li> <li>• ALL: Operating the RST key or power is turned on again.</li> </ul>	Yes	Yes
Protect Level (Index 102: Protect Level)	Restricts reading/writing of setting data and monitor operations in four levels. The factory default is Level 1.	Yes	Yes
Channel ON/OFF Key Enable/Disable (Index 103: CH Key)	Allows connection/disconnection switching via the Channel ON/OFF key. This function can be disabled to prevent incorrect operation. The default setting is Enabled.	Yes	Yes
Initialize Settings (Index 2: System Command)	Used to restore all settings to their default values.	Yes	Yes

For details, refer to 4-3 *Parameter Settings in Setting Mode* in the *S8NR-S Users Manual* (Man. No. T245).

### Monitor Mode and Setting Mode of the S8NR-S

At shipment, all branch outputs are connected (ON), and the unit starts in Monitor Mode.

To disconnect unused branch outputs, use the Channel ON/OFF key.

Various parameters can be changed in Setting Mode.

## Displaying Alarms

The S8NR-S displays alarms according to the parameters set in Setting Mode. The alarm number and detected value are alternated on the display for each item.

Error code	Error	Output status
A10	Abnormal Voltage Tripping	Cut off All branch outputs
A11	Abnormal current tripping	Cut off the Target Outputs
A12	Total output current tripping	Cut off all branch outputs
A21	Undervoltage detection	No cutoff operation
A23	Replacement time notification	No cutoff operation
A23/HOT	Overheating alarm	No cutoff operation
A30	Over-temperature output	No cutoff operation

## Resetting Alarms

When an alarm is displayed, remove the cause of the alarm and then press the RST/ESC Key. When it is possible to clear the error, press the RST/ESC Key for 3 seconds. RST will be shown on the 11-segment display. Resetting will be possible.

**Note: 1.** Although errors are normally cleared when the power supply is turned ON, the setting of a parameter can be changed so that errors are not cleared.

**Note: 2.** The over-temperature output will automatically be reset when the temperature drops below the set value.


## Operation display and how to operate the Channel ON/OFF key

The output status of branch outputs is displayed using LED illumination.

Refer to the *S8NR-S User's Manual* (Man. No. T245) for the procedure to recover from an abnormal condition.

Lights in green	Normal connected state
Flashes in green	Connection standby state by startup sequence
Lights in red	Abnormal shutdown status (waiting for recovery).
Flashes in red	Abnormal disconnection status (operation not possible)
Off	Disconnection or Operation stopped state to forced operation

**Note:** If the "Channel ON/OFF key" does not respond, check if the parameter "Channel ON/OFF key Enabled/Disabled" is set to "Disabled". (Default value: Enabled)




\*1. If the Startup sequence settings is 0s, it will connect normally without waiting.

\*2. If switching ON/OFF continuously, the channel will not switch from OFF to ON unless more than 3 seconds have passed since the last ON.

\*3. In the case of a tripping status due to an internal fault (waiting for recovery), it will blink Red at 0.25-second intervals.

**Error Display List**

Seven-segment display	Error code	Meaning	Probable cause and remedy	
$\text{E}rP$	ERP	Memory error on power supply side	These are S8NR-S system errors. When one of these error codes is displayed, check the system configuration and clear the error, and then turn the power supply OFF and ON again. If the error code persists, contact your OMRON representative regarding the error.	
.	---	S8NR-S hardware error		
$\text{E}98$	E98	RAM error		
$\text{E}97$	E97	EEP-ROM read error		
$\text{E}96$	E96	EEP-ROM write error		
$\text{E}94$	E94	Short circuit failure		
$\text{E}00$	E00	EEP-ROM initialization error		
$\text{E}01$	E01	EEP-ROM error		
$\text{E}02$	E02	Model error		
$\text{E}03$	E03	Factory default detection mode		
$\text{E}06$	E06	Product overheating abnormality	An overheating state has continued for over 180 minutes.	Internal components may have degraded, so replace the main unit.
$\text{E}10$	E10	Data is corrupted.	There is an error in the parameter settings.	Press the Mode Key to switch to the parameter initialization display. After initializing the parameters, set them again.
$\text{A}10$	A10	Abnormal Voltage Tripping	The power supply voltage has exceeded the abnormal voltage tripping threshold.	Check the power supply voltage.
$\text{A}11$	A11	Abnormal current tripping	The current of the Branch output has reached an abnormal current cutoff judgment.	Check whether the connected device is correct and check whether the set value is appropriate.
$\text{A}12$	A12	Total current tripping	All branch outputs were cutoff, since the specified total current value and its power-ON time (s) exceeded the total abnormal current tripping condition.	Check whether the connected devices are appropriate and whether they are being used within the total current value for all branch outputs that were tripped.
$\text{A}21$	A21	Undervoltage alarm	The output voltage dropped below the undervoltage detection threshold.	Check the power supply voltage and the set value.
$\text{A}23$	A23	The unit for this is displayed in 2 ways: Yrs or % is lit: Maintenance forecast monitor output kH is lit: Running time alarm	Indicates that the replacement time of this unit calculated within type S8NR-S has fallen below the set notification time.	The replacement time is approaching.
$\text{A}23/\text{HOT}$	A23/HOT	Overheating alarm	The S8NR-S is overheated.	Take steps to reduce the internal temperature.
$\text{A}30$	A30	Over-temperature output	The S8NR-S's internal temperature exceeded the over-temperature output threshold.	Check for a high ambient temperature and check the setting of the over-temperature output threshold. Take steps to reduce the temperature in the control panel.
$\text{S}tb$	---	Standby function active.	The output has been disabled by an operation command from IO-Link communication. Release it via IO-Link communication.	

Branch output number LED display	Error code	Meaning	Probable cause and remedy	
	---	Measurement circuit is in a standby state.	This is displayed temporarily when the power is interrupted. There is a possibility of a malfunction if it is displayed when the power is turned on. If it is displayed continuously, perform power cycling. If the abnormality still occurred, contact your OMRON representative regarding the error.	

- When multiple abnormalities occur simultaneously, they are displayed in priority order from top to bottom in the table above.
- An A11 abnormality may occur simultaneously on two or more branch outputs. In this case, the branch output number LED for the A11 abnormality that occurred later will not be displayed.


Dimensions

(Unit: mm)

Main Unit

90 W


S8NR-S09024-A1L0



360 W/600 W

S8NR-S36024

S8NR-S60024






Note: S8NR-S60024-A2L2-IL3 (shown above)

S8NR-S




S8R-BB

**Mounting Brackets**

DIN Rail mounting brackets  
S82Y-NRS01DIN





S82Y-NRS02DIN



**Connector cover**

**Waterproof caps**


XS5Z-12 and XS5Z-13 have Smartclick mechanism. There's no need to keep track of locking torque.

Appearance	Model	Material	Suitable Connectors for S8NR-S	Mounting part
	XS5Z-12	PBT	Output terminals	M12 female screw
	XS5Z-13	PBT	Input terminals, IO-Link communication terminals, Signal output terminals	M12 male screw

**Rain Mounting (order separately)**

**Support rail (Material: Aluminum)**


PFP-100N  
PFP-50N



Model
PFP-100N
PFP-50N

**Support rail (Material: Aluminum)**


PFP-100N2



Model
PFP-100N2

**End Plate**

PFP-M




Model
PFP-M

**Tools for M12 threaded connectors**

The S8NR-B/S8R-BB supports the use of M12 screw-type connectors. Use them to tighten the fixture of the M12 threaded connector to the specified torque value.

**Torque Wrench**  
XY2F-0004





# S8NR-S





## Connector Cables

### Cable for Input Connector

Available in July 2026



Appearance	Specification	Connector	Cable connection direction	No. of cable conductors	Cable length	Model
	M12 socket (S-coding, Female) -M12 Plug (S-coding, Male)	Smartclick	Straight/ straight	3	0.5	XS5W-S321-B22-F
					1	XS5W-S321-C22-F
					2	XS5W-S321-D22-F
					3	XS5W-S321-E22-F
					5	XS5W-S321-G22-F
					10	XS5W-S321-J22-F
					15	XS5W-S321-K22-F
					20	XS5W-S321-L22-F
	M12 socket (S-coding, Female) -Flying leads	Smartclick	Straight/ straight	3	0.5	XS5F-S321-B22-F
					1	XS5F-S321-C22-F
					2	XS5F-S321-D22-F
					3	XS5F-S321-E22-F
					5	XS5F-S321-G22-F
					10	XS5F-S321-J22-F
					15	XS5F-S321-K22-F
					20	XS5F-S321-L22-F

### Cable for Output Connector (M12, A-coded)





Appearance	Specification	Connector	Cable connection direction	No. of cable conductors	Cable length	Model
	M12 socket (A-coding, Female) -M12 Plug (A-coding, Male)	Smartclick	Straight/ straight	4	0.5	XS5W-D421-B81-F
					1	XS5W-D421-C81-F
					2	XS5W-D421-D81-F
					3	XS5W-D421-E81-F
					5	XS5W-D421-G81-F
					10	XS5W-D421-J81-F
					15	XS5W-D421-K81-F
					20	XS5W-D421-L81-F
				5	0.5	XS5W-D521-BG1-F
					1	XS5W-D521-CG1-F
					2	XS5W-D521-DG1-F
					3	XS5W-D521-EG1-F
					5	XS5W-D521-GG1-F
					10	XS5W-D521-JG1-F
					15	XS5W-D521-KG1-F
					20	XS5W-D521-LG1-F
	M12 Plug (A-coding, Male) -Flying leads	Smartclick	Straight/ straight	4	0.3	XS5H-D421-A80-F
					0.5	XS5H-D421-B80-F
					1	XS5H-D421-C80-F
					2	XS5H-D421-D80-F
					3	XS5H-D421-E80-F
				5	0.5	XS5H-D521-BG0-F
					1	XS5H-D521-CG0-F
					2	XS5H-D521-DG0-F
					3	XS5H-D521-EG0-F
					5	XS5H-D521-GG0-F

**Cable for Output Connector (M12, L-coded)**

Available in July 2026

Appearance	Specification	Connector	Cable connection direction	No. of cable conductors	Cable length	Model
	M12 socket (L-coding, Female) -M12 Plug (L-coding, Male)	Smartclick	Straight/ straight	5	0.5	XS5W-L521-B12-F
					1	XS5W-L521-C12-F
					2	XS5W-L521-D12-F
					3	XS5W-L521-E12-F
					5	XS5W-L521-G12-F
					10	XS5W-L521-J12-F
					15	XS5W-L521-K12-F
	M12 Plug (L-coding, Male) -Flying leads	Smartclick	Straight/ straight	5	0.5	XS5H-L521-B12-F
					1	XS5H-L521-C12-F
					2	XS5H-L521-D12-F
					3	XS5H-L521-E12-F
					5	XS5H-L521-G12-F
					10	XS5H-L521-J12-F
					15	XS5H-L521-K12-F
					20	XS5H-L521-L12-F

**Cable for IO-Link Communication Connection**



Appearance	Specification	Connector	Cable connection direction	No. of cable conductors	Cable length	Model
	M12 socket (A-coding, Female) -M12 Plug (A-coding, Male)	Smartclick	Straight/ straight	4	0.5	XS5W-D421-B81-F
					1	XS5W-D421-C81-F
					2	XS5W-D421-D81-F
					3	XS5W-D421-E81-F
					5	XS5W-D421-G81-F
					10	XS5W-D421-J81-F
					15	XS5W-D421-K81-F
				5	0.5	XS5W-D521-BG1-F
					1	XS5W-D521-CG1-F
					2	XS5W-D521-DG1-F
					3	XS5W-D521-EG1-F
					5	XS5W-D521-GG1-F
					10	XS5W-D521-JG1-F
					15	XS5W-D521-KG1-F
	M12 socket (A-coding, Female) -Flying leads	Smartclick	Straight/ straight	4	0.5	XS5F-D421-B80-F
					1	XS5F-D421-C80-F
					2	XS5F-D421-D80-F
					3	XS5F-D421-E80-F
					5	XS5F-D421-G80-F
					10	XS5F-D421-J80-F
					15	XS5F-D421-K80-F
				5	0.5	XS5F-D521-BG0-F
					1	XS5F-D521-CG0-F
					2	XS5F-D521-DG0-F
					3	XS5F-D521-EG0-F
					5	XS5F-D521-GG0-F
					10	XS5F-D521-JG0-F
					15	XS5F-D521-KG0-F
					20	XS5F-D521-LG0-F

# Safety Precautions





S8NR-S

S8R-BB


Refer to *Safety Precautions for All Power Supplies*.  
Warning Indications


 <b>WARNING</b>	Warning Level Indicates a potentially hazardous situation which, if not avoided, will result in minor or moderate injury, or may result in serious injury or death. Additionally, there may be significant property damage.
 <b>CAUTION</b>	Caution level Indicates a potentially hazardous situation which, if not avoided, may result in minor or moderate injury or in property damage.
<b>Precautions for Safe Use</b>	Supplementary comments on what to do or avoid doing, to use the product safely.
<b>Precautions for correct use</b>	Supplementary comments on what to do or avoid doing, to prevent failure to operate, malfunction or undesirable effect on product performance.

## Meaning of Product Safety Symbols

	General instructions Used for general mandatory action precautions for which there is no specified symbol.
	Caution against electric shock Used to warn of the risk of electric shock under specific conditions.
	Caution against high temperatures Used to warn of the risk of minor injury caused by high temperatures.
	No disassembly Use to indicate prohibition when there is a risk of minor injury from electrical shock or other source if the product is disassembled.

## CAUTION

Minor electric shock, fire, or Product failure may occasionally occur. Do not disassemble, modify, or repair the Product or touch the interior of the Product. 

Minor burns may occasionally occur. Do not touch the Product while power is being supplied or immediately after power is turned OFF. 

## Precautions for Safe Use

### Installing/Storage Environment

- Store the Product at a temperature of -25 to 85°C and a humidity of 5 to 95% or less.
- To maintain the performance of the maintenance forecast monitor, store the Product at a temperature of -20 to 30°C and a relative humidity of 25 to 70% when storing it for more than three months. (360 W/600 W)
- When installing the Product, ensure adequate heat dissipation to improve the long-term reliability of the equipment. Be sure to allow sufficient air circulation around the Product, and use the Product within the derating curves.
- The internal parts may occasionally deteriorate or be damaged. Do not use the Product in areas outside the derating curves.
- Internal parts may possibly be damaged. Do not use a current that exceeds the rated total output current of the power supply. If temporary peak currents occur repetitively, design the system so that the peak values do not exceed the peak load conditions. (360 W/600 W)
- Use the Product in locations with a relative humidity of 5 to 95% or less.
- Do not use the Product in low dew point environments.
- Do not use the Product outdoors or where it would be subjected to direct sunlight.
- Do not use the Product where it would be subjected to shock or vibration. A device such as a contact breaker may be a vibration source. Set the Product as far as possible from possible sources of shock or vibration.
- To prevent an accident due to the product falling, wear appropriate protective gear such as safety shoes, safety glasses, and a helmet when performing installation or replacement work.
- Due to degraded heat dissipation and loss of protective structure, internal parts may occasionally deteriorate or be damaged. Do not loosen the screws on the power supply unit.
- If the Product is used in an area with excessive electronic noise, be sure to separate the Product as far as possible from the noise sources.
- Do not use the Product in locations where oil mist is present.
- Do not use the Product in locations where it may be exposed to high-pressure water.
- Do not use the Product in locations where spatter may occur.
- Do not use the Product in locations where corrosive or volatile gases are generated.
- Avoid installing the Product in locations where the temperature changes rapidly, such as near exhaust outlets.
- Do not use the Product at altitudes above 3,000 m, as the protective structure may not be maintained.
- Do not use detergents or chemicals for cleaning.
- Do not connect a battery or other backup power supply to the output of the Product.
- Although some inverters have an output frequency of 50/60 Hz, they may cause internal temperature to rise and result in damage, if they are connected as the power source for the S8NR-S. Do not use the output from an inverter as the power source for the S8NR-S.
- When connecting a UPS to the input, do not use a UPS with a rectangular-wave output. A rise in internal temperature may cause smoke or malfunction.
- Do not use this Product as a foothold.
- Avoid contact with the Product when passing nearby.

## Installation/Wiring

- Be sure to connect the ground completely. Because this is a PE (Protective Earth) terminal (⊕) specified by safety standards, electric shock or malfunction may occur if the grounding is incomplete.

**Note:** The protective earthing required for safety can be ensured only by the PE terminal (⊕) of the input terminal (1). Use the PE terminal (⊕) as required.

- Minor fire may possibly occur. Ensure that input and output terminals are wired correctly.
- To prevent wiring materials from smoking or ignition, use the wiring materials given in the following table.

### Recommend Cables:

Terminal (Main Unit side)	Connector Main Unit side	Recommended cables	
		Both-end connector	One-end connector
Input Terminal	M12-S (Plug)	XS5W-S321-□22-F	XS5F-S321-□22-F
Output Terminal	M12-A (Socket)	XS5W-D421-□81-F XS5W-D521-□G1-F	XS5F-D421-□80-F XS5F-D521-□G0-F
	M12-L (Socket)	XS5W-L521-□12-F	XS5H-L521-□12-F
IO-Link Communication Terminal	M12-A (Plug)	XS5W-D421-□81-F XS5W-D521-□G1-F	XS5H-D421-□80-F XS5H-D521-□G0-F
Signal Terminal	M12-A (Plug)	XS5W-D421-□81-F XS5W-D521-□G1-F	XS5H-D421-□80-F XS5H-D521-□G0-F

Use copper wires. Use stranded wire or solid wire (heat resistance: 75°C or higher).

- Do not insert or remove the Smart Click connector more than the durability limit of 50 cycles.

## Branch Output (360 W/600 W)

- Do not repeat cutoff and recovery operations more than necessary, because internal components may deteriorate or be damaged.
- Cutoff performance is guaranteed according to the ambient temperature. Do not use the Product outside the derating curves.

## Output Voltage Adjustment

Default Setting: Set at the rated voltage

(90 W)

Output voltage adjustment is not available.

(360 W/600 W)

Adjustment Range: The output voltage can be adjusted from 24 to 28 VDC using the Select Down Key/Select Up Key on the front panel.

- Adjust the output voltage using "V-O" in the setting mode.
- When decreasing the output voltage, the undervoltage alarm function may operate depending on its setting value.
- After adjusting the output voltage, ensure that the total output power and output current of each branch output do not exceed the rated output power and rated total output current.


For details, refer to the user's manual.

## Peak Current (360 W/600 W)

Peak current is the current that can exceed the rated current for a limited period of time. The Product can be used within the range that satisfies the following five conditions:

- Peak-current duration:  $t_1 \leq 5$  s
- Peak current:  
 $I_p \leq \text{Maximum Peak Current} = \text{Rated Total Output Current} \times 150\%$
- Average output current:  $I_{ave} \leq \text{Rated Total Output Current} \times 80\%$
- Peak-current duty ratio:  $\text{Duty} \leq 10\%$
- $\text{Duty} = T_1 / (t_1 + t_2) \times 100 [\%] \leq 10\%$

The Product can be used at the rated current after completion of the  $t_2$  period.



- Do not allow peak current to continue for more than 5 seconds. Also, do not exceed a 10% duty ratio. Doing so may cause Product damage.
- Do not allow the average current over one peak current cycle to exceed 80% of the rated total output current. Product damage may occur.
- Reduce the peak current and average output current depending on the ambient operating temperature and installation conditions.

**Precautions for Correct Use**


For information on detailed settings, refer to the User's Manual.

- The service life of the power supply is determined by the lifetime of the electrolytic capacitors used inside the unit. According to the Arrhenius law, also known as the "10°C-half-life rule," the lifetime of a capacitor is reduced to one-half when the ambient temperature increases by 10°C, and doubles when the ambient temperature decreases by 10°C. Therefore, lowering the internal temperature of the power supply extends its service life.


**Mounting**

- Mounting Direction  
Mount the S8NR-S unit as below.


**Standard mounting**




- \*1. Top, bottom, left, right, and front: 15 mm min.
- \*2. Secure sufficient space in consideration of cable mounting. Example: For the OMRON cable type XS5, provide approx. 150 mm.




Standard mounting




Horizontal mounting (90° clockwise)




Horizontal mounting (90° counterclockwise)



Inverted mounting



Downward mounting



Upward mounting

- The S8NR-S type is a wall-mount product and refer to the Mounting hole machining dimensions when installing the unit.
- When mounting the Product, ensure sufficient space for heat dissipation and wiring.

**Input Voltage Tolerance**

90 W

- Rating: 100 to 240 VAC
- Allowable AC input range: -15 to 10% (85 to 264 VAC)
- When using an input voltage less than 100 VAC, reduce the load calculated with derating 1%/V.

360 W

- Rating: 100 to 240 VAC
- Allowable AC input range: -15 to 10% (85 to 264 VAC)
- When using an input voltage less than 100 VAC, reduce the load calculated with derating 1%/V.

600 W

- Rating: 200 to 240 VAC
- Allowable AC input range: -15 to 10% (170 to 264 VAC)
- When using an input voltage less than 200 VAC, reduce the load calculated with derating 0.5%/V.

**Overcurrent Protection (90 W)**

The overcurrent protection circuit automatically reduces the output voltage in the event of a short circuit or overcurrent, thereby protecting the Product itself. When the overcurrent condition is removed, the Product automatically returns to normal operation. Internal parts may deteriorate or be damaged in rare cases. Do not use this Product in applications where inrush current or overload conditions frequently occur on the load side.

**Overvoltage Protection (90 W)**

The Product detects an overvoltage condition to prevent excessive voltage from being applied to the load due to a failure of the internal feedback circuit or other causes. If an excessive voltage of approximately 130% or more of the rated output voltage is output, the output voltage is cut OFF. To restore operation, turn the input power OFF, wait for at least 3 minutes, and then turn the input power ON again.

**DC OK Signal Output (90 W)**

When the output voltage is 90% or more of the rated output voltage, the internal MOS FET relay turns ON (conducts).

- MOS FET relay outputs: 30 VDC max., 50 mA max., residual voltage when ON: 2 V max., leakage current when OFF: 0.1 mA max.
- Wire all output signal circuits correctly. Internal current control circuits are not provided internally for output signals. Do not allow the output current to exceed 50 mA.
- After completing wiring, confirm that the circuits operate correctly.

**Abnormal Voltage Tripping (360 W/600 W)**

1. The S8NR-S has an abnormal voltage tripping function. When the output voltage exceeds the set value, all branch outputs are shut off. However, this function does not protect the load or internal parts from high voltages in all situations. Use the output voltage within the rated range.
2. Outputs may be cut off by the abnormal voltage protection with loads that generate reverse peak electromotive force.

**Abnormal Current Tripping (360 W/600 W)**

The S8NR-S has an abnormal current tripping function. A branch output will be cut off if its current exceeds a preset value. Also, all branch outputs will be cut off if their total peak output current exceeds a specified value.

- Note: 1.** Continuing operation with overcurrent may occasionally result in deterioration or destruction of internal elements.
- Note: 2.** Do not use the Power Supply Unit for applications in which load inrush current or overload will frequently occur. Doing so may result in deterioration or damage to internal components.

## Maintenance Forecast Monitor Function (360 W/600 W)

The accuracy of the maintenance forecast monitor function and the accumulated operating time may be reduced in applications where the AC input turns ON and OFF frequently. Under general usage conditions, the S8NR-S will reach the replacement notification threshold in a few years to over a decade. For long-term use, regularly check that the replacement period does not fall below 0.5 years by monitoring the display or by confirming it through communication.

## Startup Sequence and Shutdown Sequence Function (360 W/600 W)

When using multiple units of this product, the sequence function is guaranteed between branch outputs within a single unit, but time synchronization between units cannot be achieved.

## Dielectric Strength Test

(90 W)

The S8NR-S is designed to withstand 2,000 VAC for 1 minute between <input terminal (1), pins 1 and 3 grouped together> and <PE terminal ⊕, output terminals, and signal terminals (2) (3) grouped together>.

When performing the withstand-voltage test, set the cutoff current of the hipot tester to 20 mA.

(360 W)

The S8NR-S is designed to withstand 2,000 VAC for 1 minute between <Input terminal (1) pins 1 and 3 (grouped)> and <PE terminal ⊕, branch output terminals and IO-Link communication terminals (grouped) (2), (3), and (4)>. When performing the withstand-voltage test, set the cutoff current of the hipot tester to 20 mA.

**Note: 1.** The S8NR-S may possibly be damaged from the impulse voltage if a testing device switch is used to abruptly apply or shut off 2,000 VAC. Increase the applied voltage gradually using the voltage adjustment on the testing device.

**Note: 2.** When testing terminals together, always short the specified terminals so that the voltage is applied to all of the terminals at the same time.

## Insulation Resistance Test

When testing the insulation resistance, use a DC resistance meter at 500 VDC.

**Note:** When performing the test, be sure to short-circuit all output terminals(+, -) and signal terminals to prevent damage.

## No Output Voltage

The internal circuit's overcurrent protection or overvoltage protection may operate. Alternatively, the latch protection circuit may operate if there is a lightning surge or other large voltage applied to the input. Contact OMRON if there is still no output voltage after checking the following two points:

- Checking Overcurrent Protection  
Check whether the load is in an overcurrent or short-circuited state. Remove the wires to the load before checking.
- Checking Overvoltage Protection and Latching Protection  
Turn the power supply OFF and leave it OFF for at least 3 minutes, then turn it ON again.
- When the tripping alarm output operates, always remove the cause of the output first and then reset the alarm.
- When cycling the input power supply, always remove any problems first and then turn ON the input power supply.
- If short-circuit or overcurrent conditions continue, internal parts may occasionally deteriorate or be damaged.

## Displaying the Output Voltage (360 W/600 W)


The voltage detection function monitors the voltage inside the circuit after AC/DC conversion.

The displayed voltage will differ slightly from the value at the power supply output terminals due to internal voltage drop.

To accurately confirm the output voltage, measure the voltage at the output connector.

## Prohibition of Parallel Connection

Do not connect branch outputs from the S8NR-S in parallel (360 W/600 W). Also, do not connect the branch outputs in parallel with branch outputs of other S8NR-S Units.



Parallel connection with other Branch output circuits is Not supported.

## Mounting Bracket (Optional)


Always use the screws provided as accessories.

Recommended tightening torque for mounting screws: 0.5 to 0.6 N·m

## Disposal

When disposing of the item, treat the S8NR-S as industrial waste.

## Inrush current, startup time, Outputs hold time



**Note:** When N units are used via branch connectors or similar means, an inrush current equal to N times that of single-unit operation will flow. In particular, to prevent external fuses from blowing or breakers from not operating due to the inrush current, thoroughly check the blowing characteristics of the fuses and the operating characteristics of the breakers, and select them accordingly.


## Connectors and Cables

Install using a torque not exceeding the specified value.


- The proper tightening torque for M12 connectors is 0.39 to 0.49 N·m.
- For M12 Smart Click connector engagement, securely tighten by hand until the engagement completion mark is reached.
- Always turn off the power before connecting or disconnecting connectors.
- Do not forcibly bend or pull the cable. Do not place heavy objects on the cable sheath, as this may cause disconnection.

### Smartclick installation method

1. Align the polarity key inside the connector and insert the projection on the plug fully into the groove on the socket.



2. Rotate the cable retainer approximately 1/8 turn to the right. When you feel or hear a 'click,' the coupling is complete. You can also confirm by checking the coupling marks on the plug and socket.



### Conformance to EU and UK Directives

Refer to the datasheet and instruction manual for details on the operating conditions for EMC compliance.

**Warning:** When IO-Link Communication is used, the S8NR-S is Class A product. In a residential, commercial, or light industrial environment, it may cause radio interference. The S8NR-S is not intended to be installed in a residential environment. In a commercial or light industrial environment with connection to a commercial power supply, the user may be required to take adequate measures to reduce interference.



**OMRON AUTOMATION AMERICAS HEADQUARTERS** • Chicago, IL USA • 847.843.7900 • 800.556.6766 • automation.omron.com

**OMRON CANADA, INC. • HEAD OFFICE**

Toronto, ON, Canada • 416.286.6465 • 866.986.6766 • automation.omron.com

**OMRON ELECTRONICS DE MEXICO • HEAD OFFICE**

Ciudad de México • 52.55.5901.4300 • 01.800.386.6766 • mela@omron.com

**OMRON GUADALAJARA**

Torre NIBA Av. de las Américas 1462, Country Club, 44610, Piso 8,  
Guadalajara, Jal. Tel. 55.5901.4300

**OMRON ELETRÔNICA DO BRASIL LTDA • HEAD OFFICE**

São Paulo, SP, Brasil • 55 11 5171-8920 • automation.omron.com

**OMRON ARGENTINA • SALES OFFICE**

Buenos Aires, Argentina • +54.11.4521.8630 • +54.11.4523.8483  
mela@omron.com

**OTHER OMRON LATIN AMERICA SALES**

+54.11.4521.8630 • +54.11.4523.8483 • mela@omron.com

**Controllers & I/O**

- Machine Automation Controllers (MAC) • Motion Controllers
- Programmable Logic Controllers (PLC) • Temperature Controllers • Remote I/O

**Operator Interfaces**

- Human Machine Interface (HMI)

**Motion & Drives**

- Machine Automation Controllers (MAC) • Motion Controllers • Servo Systems
- Frequency Inverters

**Vision, Measurement & Identification**

- Vision Sensors & Systems • Measurement Sensors • Auto Identification Systems

**Sensing**

- Photoelectric Sensors • Fiber-Optic Sensors • Proximity Sensors
- Rotary Encoders • Ultrasonic Sensors

**Safety**

- Safety Light Curtains • Safety Laser Scanners • Programmable Safety Systems
- Safety Mats and Edges • Safety Door Switches • Emergency Stop Devices
- Safety Switches & Operator Controls • Safety Monitoring/Force-guided Relays

**Control Components**

- Power Supplies • Timers • Counters • Programmable Relays
- Digital Panel Meters • Monitoring Products

**Switches & Relays**

- Limit Switches • Pushbutton Switches • Electromechanical Relays
- Solid State Relays

**Software**

- Programming & Configuration • Runtime